



home  
automation



lighting



electric



furniture

**ORNO**<sup>®</sup>

LIVING INNOVATIONS



## DATA SHEET

DIN rail power adaptor 24VDC, 4A, 100W, width: 4  
units

symbol: OR-PSU-1649

**Manufacturer:**  
ORNO-LOGISTIC Sp. z o.o.  
ul. Rolników 437, 44-141 Gliwice  
tel: 32 43 43 110  
www.orno.pl

ISBN 5908254803901



5 908254 803901 >

## The main features:

Highly efficient and reliable DIN rail power adaptor of 100W max. load and 24V DC output voltage, which can be adjusted. It has been developed for DIN rail installation and can be used in vast number of applications, e.g. industrial applications, low voltage installations, such as CCTV or alarm systems. This power adaptor includes: overload protection, anti-surge protection and overvoltage protection. An integrated diode indicates activation of the device.



OUTPUT VOLTAGE:  
24V DC



OUTPUT CURRENT:  
4A



RATED POWER:  
96W



INPUT VOLTAGE:  
100-230V  
50-60Hz



INSTALLATION:  
na szynę DIN



SZEROKOŚĆ ILOŚĆ  
MODUŁÓW:  
4

## Technical specifications:

### General Information

Output voltage:	24V DC
Output current:	4A
Rated power:	96W
Max. prąd chwilowy:	4,6A
Input voltage:	100-230V 50-60Hz
Protection rating:	IP20

Installation:	na szynę DIN
Regulacja napięcia:	✓ yes
Zabezpieczenie przeciwzwarciowe:	✓ yes
Zabezpieczenie prądowe:	✓ yes
Zabezpieczenie napięciowe:	✓ yes
Pobór mocy w stanie spoczynku:	0,3W
Szerokość ilość modułów:	4
Dimensions (width x height x depth [mm]):	70 / 90 / 58