



home
automation



lighting



electric



furniture

ORNO[®]

LIVING INNOVATIONS



DATA SHEET

DIN rail power adaptor 12V DC 1.25A, 15W, width:
1 unit

symbol: OR-PSU-1642

Manufacturer:
ORNO-LOGISTIC Sp. z o.o.
ul. Rolników 437, 44-141 Gliwice
tel: 32 43 43 110
www.orno.pl

ISBN 5908254803833



5 908254 803833 >

The main features:

Highly efficient and reliable DIN rail power adaptor of 15W max. load and 12V DC output voltage, which can be adjusted. It has been developed for DIN rail installation and can be used in vast number of applications, e.g. industrial applications, low voltage installations, such as CCTV or alarm systems. This power adaptor includes: overload protection, anti-surge protection and overvoltage protection. An integrated diode indicates activation of the device.



OUTPUT VOLTAGE:
12V DC



OUTPUT CURRENT:
1,25A



RATED POWER:
15W



INPUT VOLTAGE:
100-230V
50-60Hz



INSTALLATION:
na szynę DIN



SZEROKOŚĆ ILOŚĆ
MODUŁÓW:
1

Technical specifications:

General Information

Output voltage:	12V DC
Output current:	1,25A
Rated power:	15W
Max. prąd chwilowy:	2,1A
Input voltage:	100-230V 50-60Hz
Protection rating:	IP20

Installation:	na szynę DIN
Regulacja napięcia:	✓ yes
Zabezpieczenie przeciwzwarciowe:	✓ yes
Zabezpieczenie prądowe:	✓ yes
Zabezpieczenie napięciowe:	✓ yes
Pobór mocy w stanie spoczynku:	0,3W
Szerokość ilość modułów:	1
Dimensions (width x height x depth [mm]):	18 / 90 / 58